

LANSEN

Door and window detector with including magnet

LAN-WMBUS-M2

DEVICE

The Lansen door and window device alerts as soon as a door or window is opened or closed thanks to its internal onboard reed relay. The functionality can be increased further by adding an external reed relay and magnet to monitor, for example, another window.

Much care have been taken to design a sleek, good looking device with high security and performance. The design allows for discrete integration when installed in home environment.

PERFORMANCE

Three message are sent successively if the device detects if a window or door has been opened or closed, this to ensure at least one message is received by a gateway.

The battery level is continuously monitored and a low level warning is issued when battery is nearing depletion.

FIRMWARE

MODES	Configurable C-, T- or S-mode (Selectable on order)
SEND INTERVAL	Configurable 60s - 1 hour (selectable on order)
ENCRYPTION	AES128 encryption OMS mode 5, Profile A. Configurable ON/OFF, unique key (selectable on order)
<u>STANDARD</u>	T1-Mode, 90 seconds, encryption ON. and as soon a door / windows has closed / opened

WARNINGS

MAGNET DETECTION	Door or window was opened or closed
BATTERY	Low battery

POWER/LIFETIME

POWER SUPPLY	ER14505 3.6V Li-SOCI2 battery
VOLTAGE	2.4 to 3.6V
LIFESPAN	14* years typical, standard configuration and operating temperature.
RADIO	14 dBm (25 mW) output power to antenna. ERP typical: 13 dBm (19.95 mW)

GENERAL INFORMATION

STANDARDS	2014/53/EU (RED) EN 13757-3/4:2013, OMS 4.0.2
MATERIAL	White, ABS
SIZE (W x L x D)	
TRANSMITTER	25.5 x 105 x 22 mm
MAGNET	16 x 65 x 18 mm

OPERATING CONDITIONS

RADIO TRANSMITTER	Max: -30°C to +85°C Recomended +5°C to +50°C
RELATIVE HUMIDITY	None condensing

DEVICES

LAN-WMBUS-M2	Door and window device
--------------	------------------------

ACCESSORIES

External cable connected reed relay
Lansen configuration USB-cable

MEASUREMENTS

The total number of openings and current opening status is sent periodically. The sensor also sends three message as soon as it detects a change in status (door/window have been opened/closed). This makes the sensor ideal for integration in data collecting systems, for energy management, HVAC-control, or for knowing if doors are opened or closed.

The data from the device is protected using the AES128 encryption compliant with OMS standard.

EXTERNAL REED RELAY WITH MAGNET

An external reed relay can be connected to the device so that another window or door can be monitored. In other words, by adding an external reed relay, up to two windows/doors can be monitored and the device will alert if one of them are opened or closed.

CONFIGURATION

The MBUS mode, transmission interval and encryption can be configured using a Lansen configuration USB-cable.



* The expected battery lifetime stated is based on simulations and true measurements at 25°C and is valid to the best of our ability but not a guarantee. The calculations and measurements can be sent upon request for your reference.